

## SECTION A



## INTEGRAL AC MOTORS

## Three-phase 4 poles (~1450 rpm at 50Hz)

Frame size	Maximum Power (S3 40%)	Assembly code	Spare motor code	Ø A	B	C	L	Weight kg
71	0,37kW (0,5HP)	N0,37AC 34 71	N037AC341S3	15	138	180	210	5,5
	0,55kW (0,75HP)	N0,55AC 34 71	N055AC341S3	15	138	180	210	5,5
	0,75kW (1HP)	N0,75AC 34 71	N075AC341S3	15	138	180	210	5,5

## Three-phase 2 poles (~2900 rpm at 50Hz)

Frame size	Maximum Power (S3 40%)	Assembly code	Spare motor code	Ø A	B	C	L	Weight kg
71	0,55kW (0,75HP)	N0,55AC 32 71	N055AC321S3	15	138	180	210	5
	0,75kW (1HP)	N0,75AC 32 71	N075AC321S3	15	138	180	210	5

## Single-phase 4 poles (~1450 rpm at 50Hz)

Frame size	Maximum Power (S3 40%)	Assembly code	Spare motor code	Ø A	B	C	L	Weight kg
71	0,37kW (0,5HP)	N0,37AC S4 71	N037ACS41S3	15	138	180	210	6,5
	0,55kW (0,75HP)	N0,55AC S4 71	N055ACS41S3	15	138	180	210	7,2

## Single-phase 2 poles (~2900 rpm at 50Hz)

Frame size	Maximum Power (S3 40%)	Assembly code	Spare motor code	Ø A	B	C	L	Weight kg
71	0,55kW (0,75HP)	N0,55AC S2 71	N055ACS21S3	15	138	180	210	6
	0,75kW (1HP)	N0,75AC S2 71	N075ACS21S3	15	138	180	210	6,5